



AUSTRALIAN RAIL TRACK CORPORATION LTD

This document has been adopted by the ARTC with the permission of the NSW Government and will continue to apply under the authority of the ARTC General Manager Infrastructure, Strategy & Performance until further notice

Discipline
Engineering Standard - NSW

Category
Signalling

Title
Emergency Changeover Contactor Panel

Reference Number
SPS 24 - (RIC Standard: SC 09 10 02 00 SP)

Document Control

Status	Date	Prepared	Reviewed	Endorsed	Approved
Issue 1 Revision 3	May 05	Standards and Systems	Standards Engineer	GM Infrastructure Strategy & Performance	Safety Committee
		Refer to Reference Number	H Olsen	M Owens	Refer to minutes of meeting 12/08/04

Disclaimer

Australian Rail Track Corporation has used its best endeavors to ensure that the content, layout and text of this document is accurate, complete and suitable for its stated purpose. It makes no warranties, express or implied, that compliance with the contents of this document shall be sufficient to ensure safe systems of work or operation. Australian Rail Track Corporation will not be liable to pay compensation in respect of the content or subsequent use of this document for any other purpose than its stated purpose or for any purpose other than that for which it was prepared except where it can be shown to have acted in bad faith or there has been willful default.

Document Approval

The technical content of this document has been approved by the relevant ARTC engineering authority and has also been endorsed by the ARTC Safety Committee.

Document Supply and Control

The Primary Version of this document is the electronic version that is available and accessible on the Australian Rail Track Corporation Internet and Intranet website.

It is the document user's sole responsibility to ensure that copies are checked for currency against the Primary Version prior to its use.

Copyright

The information in this document is Copyright protected. Apart from the reproduction without alteration of this document for personal use, non-profit purposes or for any fair dealing as permitted under the Copyright Act 1968, no part of this document may be reproduced, altered, stored or transmitted by any person without the prior written consent of ARTC.

About This Standard

This Specification describes the general requirements for Emergency Change-Over Contactor Panels to be manufactured and supplied to Australian Rail Track Corporation or contractors to Australian Rail Track Corporation for signalling power supplies.

Document History

Primary Source – RIC Standard SC 09 10 02 00 SP Version 2.0

List of Amendments –

ISSUE	DATE	CLAUSE	DESCRIPTION
1.1	01/09/2004		Reformatting to ARTC Standard
1.2	14/03/2005	Disclaimer	Minor editorial change
1.3	06/05/2005	All	Document reformatted

Contents

1.	Introduction.....	6
2.	Applicable Documents.....	6
2.1.	ARTC Specifications	6
2.2.	Australian Standards.....	6
3.	Construction	6
4.	Specific Requirements	7
4.1.	Contactors.....	7
4.2.	Relays & Bases.....	7
4.3.	Enclosure for the Panel.....	7
4.4.	Wiring	8
4.5.	Terminals	8
4.6.	Spares To Be Provided	8
4.7.	Labelling.....	8

1. Introduction

This Specification describes the general requirements for Emergency Change-Over Contactor Panels to be manufactured and supplied to Australian Rail Track Corporation or contractors to Australian Rail Track Corporation for signalling power supplies.

Emergency Change-Over contactor panel which will be termed as "ECO panel" is used to switch 120V AC 50Hz supply from NORMAL SUPPLY to an EMERGENCY SUPPLY, in case of an interruption (or under a faulty condition) of the normal supply.

When the NORMAL SUPPLY is available the contactor will switch back to NORMAL SUPPLY.

In some instances (when normal supply is fed from a single phase off the 3 phase council supplies) a Voltage Sensing Relay shall be incorporated in the ECO panel to avoid the contactor switching back to "Normal Supply" when a fault exists on the normal supply feeder.

2. Applicable Documents

2.1. ARTC Specifications

This Specification refers to the following ARTC Specifications and Standards:

Specification. SPS 04 - General requirements Labelling of Equipment

Specification. SC 05 15 00 00 SP - Non-Vital Relays

2.2. Australian Standards

AS 3000- Electrical Installations-Building, Structures & Premises

3. Construction

Emergency Change-Over Contactor Panel shall be fabricated in accordance with Signals Standards drawing M08-489/1 and the specific requirements listed below.

Signals Standards drawing M08-489/2 shall refer to Emergency Change-Over contactor Panel (with Voltage Sensing).

4. Specific Requirements

4.1. Contactors

Selection of the contactor shall be dependant on the current ratings as specified in the Table.

Rated Current	Contactor Type	Preferred contactor for ECO Panel (“Telemechanique Type”)
50A	Block	LC1 D65008 F5
100 A	Bar	CV 1 GB
150A	Bar	CV1 GB
200A	Bar	CV1 GB
		CV1 GB

The contactors are to be fitted with (2) normally open and (2) normally closed main poles. An auxiliary contact is to be incorporated for the operation of indicators.

The contactor shall be a single block or bar type and the contactor shall be break before make type.

4.2. Relays & Bases

4.2.1 Indicating Relays

All relays used in indicating circuits shall be type "Fuji" HH23PW-T or "Omron" MK3P-I and shall be in accordance with Signals Standards Specification SC 051500 00 SP.

All bases shall be "OMRON"- PF 083A or an approved equivalent type.

4.2.2 Voltage Sensing Relay (VSR)

When specified; a voltage sensing relay shall be provided, to force the contactor to EMERGENCY SUPPLY when there is a fault on the NORMAL feeder, and to prevent the contactor from switching back until normal supply voltage is restored.

Voltage Sensing Relay shall be "Email"- 2V330 or equivalent The base for VSR shall be "Omron"- PF-083A or equivalent. The Pick-up value shall be adjusted to 115V

The Release shall be adjusted to 85% of pick-up voltage.

4.3. Enclosure for the Panel

The Panel shall be enclosed in a sheet metal case of Environmental Protection Class IP 55 with hinged front panel.

4.4. Wiring

Wiring for indicating circuits shall be done with minimum of 0.88 Sq mm (7/0.4mm) wires. All wiring shall use multi-stranded conductors and be formed and secured in a neat wire loom.

Insulation of Wires shall be rated at 90 C. Adhesive cable ties are not acceptable.

Suitable cable glands for cables up to 37/2.03 (120 Sq mm, overall dia. 21mm max.) shall be provided. All equipment shall be of front connected type.

Wire size for power conductors shall be in accordance with AS 3000.

4.5. Terminals

All conductors shall be terminated with crimp lugs either pre-insulated double-grip type for small conductors or in the case of larger conductors, non-insulated lugs with a heat shrink sleeve applied after crimping. The heat shrink sleeve shall cover the body of the crimp lug and extend at least 15mm over the conductor insulation.

All main power feed through terminals shall be "Klippon"-SAKG type or equivalent.

4.6. Spares To Be Provided

The spares to be provided are:

- A spare coil with each ECO contactor panel.
- indicating lamps - 5 No.

4.7. Labelling

Labelling for all relays, terminals and indicating lamps shall be on Traffalyte and permanently affixed (refer to Signals Standard Specification 1031-Labelling of Signalling Equipment)

The following Labels shall be provided on the front panel of the unit:

- Emergency Change-Over Contactor Panel- xxx A
- Manufacturer's name or Identity
- Date of Manufacture.

Circuit diagram of the unit shall be provided with each unit.